

# RESIDENTIAL ACCESS SOLUTIONS

## GARAGE DOOR OPENER COMPARISON CHART



	ELITE SERIES®							PREMIUM SERIES			CONTRACTOR SERIES					
Model Number	8500W	8500	WLED	85503	8550WLB	8580WLB	8587W	8360WLB	8355W	8365W-267	8160WB/8160W		8165W/8164W		8155W	8010
Description	DC Battery Backup Wall Mount Wi-Fi®	DC Battery Backup Capable Wall Mount	DC Battery Backup Belt Drive LED Wi-Fi	DC Battery Backup Belt Drive Wi-Fi with Intergrated Camera	DC Battery Backup Belt Drive Wi-Fi	DC Battery Backup Chain Drive Wi-Fi	3/4 HP AC Chain Drive Wi-Fi	DC Battery Backup Chain Drive Wi-Fi	1/2 HP AC Belt Drive Wi-Fi	1/2 HP AC Chain Drive Wi-Fi	DC Battery Backup Chain Drive Wi-Fi	DC Chain Drive Wi-Fi	1/2 HP AC Chain Drive Wi-Fi	1/2 HP AC Belt Drive Wi-Fi	DC Chain/Cable Drive	
Built-In Wi-Fi	Yes	-	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		Yes	Yes	-	
myQ® Connectivity	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	-	Yes	Yes	-	
California SB-969 Compliant*	Yes	-	Yes	Yes	Yes	Yes	-	Yes	-	-	Yes	-	-	-	-	
Security+ 2.0®, Tri-Band Radio (310, 315 and 390 MHz), Electronic Limit/ Auto-Force	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		Yes	Yes	Yes	
Battery Backup	Yes 485LM Battery	Capable 475LM Battery	Yes 485LM Battery	Yes 485LM Battery	Yes 485LM Battery	Yes 485LM Battery	-	Yes 485LM Battery	-	-	Yes 485LM Battery	-	-	-	-	
Garage Door Lock	841LM Automatic Garage Door Lock, 1 Included (2 Max.)	Automatic Deadbolt Lock** Included	841LM Automatic Garage Door Lock Capable (2 Max.)	-	841LM Automatic Garage Door Lock Capable (2 Max.)	841LM Automatic Garage Door Lock Capable (2 Max.)	841LM Automatic Garage Door Lock Capable (2 Max.)	841LM Automatic Garage Door Lock Capable (2 Max.)	-	-	-		-	-	-	
Lighting	827LM myQ Remote LED Light, 1,500 Lumens	380LM Remote Light, 2 x 100 Watts	LED, 3,100 Lumens	Side to Side, 2 x 100 Watts	Side to Side, 2 x 100 Watts	Side to Side, 2 x 100 Watts	Side to Side, 2 x 100 Watts	Front to Back, 2 x 100 Watts	Front to Back, 2 x 100 Watts	Front to Back, 2 x 100 Watts	Front, 1 x 100 Watts		Front, 1 x 100 Watts	Front, 1 x 100 Watts	Front, 1 x 60 Watts	
Soft Start/Stop	Yes	Yes	Yes	Yes	Yes	Yes	-	Yes	-	-	Yes		-	-	Yes	
Motor Vibration Isolation System (MVIS®)	-	-	-	-	-	-	Yes	-	Yes	-	-		-	-	-	
Timer-to-Close	Yes	Yes	Yes	Yes	Yes	Yes	Yes	-	-	-	-		-	-	-	
Rail	Wall Mount	Wall Mount	T-Rail System	T-Rail System	T-Rail System	I-Beam Rail System, Sensor Extension Brackets, Chassis Support Bracket	I-Beam Rail System, 2-Speed Sprocket, Sensor Extension Brackets, Chassis Support Bracket	T-Rail System	T-Rail System	T-Rail System	T-Rail System		T-Rail System		T-Rail System	Square Steel Rail (SSR) System
Control Panel	880LMW Smart Control Panel®	889LM myQ® Control Panel	880LMW Smart Control Panel	880LMW Smart Control Panel	880LMW Smart Control Panel	880LMW Smart Control Panel	880LMW Smart Control Panel	886LMW Motion Detecting Control Panel	882LMW Multi-Function Control Panel®	882LMW Multi-Function Control Panel	882LMW Multi-Function Control Panel		8165W/882LMW Multi-Function Control Panel	8164W/883LMW Door Control Button	882LMW Multi-Function Control Panel	883LMW Door Control Button
Motion Detection Light Activation	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	-	-	-		-	-	-	
LCD Programming Menu	Yes	-	Yes	Yes	Yes	Yes	Yes	-	-	-	-		-	-	-	
Light and Lock Functions	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	8165W Yes	8164W -	Yes	-	
Maintenance Alert System	Yes	-	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	8165W Yes	8164W -	Yes	-	
Pack-In Accessory	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	893LM 3-Button Remote Control	893LM 3-Button Remote Control	2 893LM 3-Button Remote Controls, 877LM Wireless Keyless Entry	893LM 3-Button Remote Control		8165W/893LM 3-Button Remote Control	8164W/891LM 1-Button Remote Control	891LM 1-Button Remote Control	891LM 1-Button Remote Control
Accessory Capacity	40 Remote Controls, 4 Wireless Keyless Entries***, 2 Automatic Garage Door Locks	12 Remote Controls, 2 Wireless Keyless Entries	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks	40 Remote Controls, 4 Wireless Keyless Entries	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks	24 Remote Controls, 2 Wireless Keyless Entries, 2 Automatic Garage Door Locks	24 Remote Controls, 2 Wireless Keyless Entries	24 Remote Controls, 2 Wireless Keyless Entries	12 Remote Controls, 1 Wireless Keyless Entry		12 Remote Controls, 1 Wireless Keyless Entry		12 Remote Controls, 1 Wireless Keyless Entry	12 Remote Controls, 1 Wireless Keyless Entry
Motor Warranty	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	Lifetime	4 Years		4 Years		4 Years	1 Year
Parts Warranty	5 Years	5 Years	5 Years	5 Years	5 Years	5 Years	5 Years	1 Year	1 Year	1 Year	1 Year		1 Year		1 Year	1 Year
Other Warranty	1-Year Battery	1-Year Battery (Optional)	Lifetime Belt, 5-Year LED, 1-Year Battery	Lifetime Belt, 1-Year Camera	Lifetime Belt, 1-Year Battery	1-Year Battery	-	1-Year Battery	Lifetime Belt	-	1-Year Battery	-	-	10-Year Belt	-	
Replacement Logic Board	050DCR.JWF	041DJ002	050DCTWFLK	050DCTWF	050DCTWFLK	041-0036	050ACTWFLK	050DCTWFLK	050ACTWF	050ACTWF	050DCTWF		050ACTWF		045ACTWF	047DCT

\*According to California SB-969, all newly sold or installed garage door openers in residential applications in California need to have battery backup beginning July 1, 2019.

\*\*8500 is not compatible with 841LM.

\*\*\*Up to 4 door controls may be wired to an opener, unless using LCD door controls, maximum 2 door controls, additional should be wireless door control model 885LM.

# RECEIVER LOGIC BOARD

## CONVERSION LIST

### OPENERS BUILT FROM 1997-2005 390 MHz SECURITY+®

MANUFACTURING DATE	DELUXE-CHAIN DRIVE	STANDARD-CHAIN DRIVE	CHAMBERLAIN® SCREW DRIVE	LIFTMASTER® SCREW DRIVE	BELT DRIVE	LIFTMASTER LOW-PROFILE SCREW DRIVE
1997	41A5021	41A5021-1		41D4674-14		
1998	41A5021-B	41A5021-1B				
1999	41A5021-C	41A5021-1C				
1999	41A5021-D	41A5021-1D		41D4674-14D	41A5021-D	
2000	41A5021-E	41A5021-1E		41D4674-14E	41A5021-5E	41A5839-1
2003	41A5021-F	41A5021-1F		41D4674-14F	41A5021-5F	41A5839-1C
2003-2005	41A5021-G	41A5021-1G		41D4674-14G	41A5021-5G	41A5839-1D
2004	41A5021-H	41A5021-1H			41A5021-5H	
2005	41A5021-I	41A5021-1I		41D4674-14H	41A5021-5I	41A5839-1E

IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:

	41A5021-I	41A5021-1I	41D4674-20	41D4764-20	41A5021-5I	41A5839-1E
--	-----------	------------	------------	------------	------------	------------

### OPENERS BUILT FROM 2001-2005 390 MHz SECURITY+

MANUFACTURING DATE	CHAIN DRIVE DELUXE END PANEL	CHAIN DRIVE STANDARD END PANEL	AC BELT DRIVE	AC CHAIN DRIVE DELUXE END PANEL DUAL CAPACITOR	DC BELT DRIVE WITHOUT BATTERY BACKUP	DC BELT DRIVE WITH BATTERY BACKUP
2001-2002	41A5483	41A5483-1	41A5483-4		41A5507	41A5507-3
2003-2005	41A5483B	41A5483-1B	41A5483-4B	41A5635	41A5507B	41A5507-6

IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:

	041A5483C	041A5483-1C	041A5483-4C	01A5635A	041A5507-B	041A5507-6C
--	-----------	-------------	-------------	----------	------------	-------------

### OPENERS BUILT FROM 2005-2014 315 MHz SECURITY+

MANUFACTURING DATE	AC CHAIN DRIVE DELUXE END PANEL	AC CHAIN DRIVE STANDARD END PANEL	AC CHAIN DRIVE DELUXE END PANEL DUAL CAPACITOR	AC CHAIN DRIVE DELUXE END PANEL SINGLE CAPACITOR	AC BELT DRIVE	DC BELT DRIVE LOW PROFILE
2005-2014	41AC050 41AC050-2	41AC050-1	41AB075-2 41AC075-2	41AC075-2S	41AB050-2	41DB001-1

IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:

	041AC050-2M	041AC050-1M	041AC075-2A	041AC075-2S	041AB050-2M	041DB001-1C
--	-------------	-------------	-------------	-------------	-------------	-------------

### OPENERS BUILT FROM 2005-2017 315 MHz SECURITY+

MANUFACTURING DATE	DC BELT DRIVE	DC SCREW DRIVE	DC WALL MOUNT MODEL 3800	AC SCREW DRIVE STANDARD	AC SCREW DRIVE STANDARD	AC SCREW DRIVE DELUXE
2005-2014	41DB001-2	41DS002-2	41DJ001	41AS050 41AS050-1	41AS050R1	41AS050R2

IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:

	041DJ001B	041DS002-2	041DJ001	041AS050-1	041AS050R1M	041AS050R2M
--	-----------	------------	----------	------------	-------------	-------------

### OPENERS BUILT FROM 2011-PRESENT 310/315/390 MHz

MANUFACTURING DATE	DC CHAIN & BELT DRIVE	AC CHAIN & BELT DRIVE	AC CHAIN & BELT DRIVE NO myQ®	DC CHAIN & BELT DRIVE WI-FI®	AC CHAIN & BELT DRIVE WI-FI	DC CHAIN & BELT DRIVE WI-FI LOCK & LED	AC CHAIN & BELT DRIVE WI-FI LOCK	DC BATTERY BACKUP WALL MOUNT WI-FI (8500W)	DC BATTERY BACKUP CAPABLE WALL MOUNT (8500)
2011-2019	45DCBL(1-5) 45DCCL(1-5) 45DCBR(1-5) 45DCCR(1-5) 045DCT 041D7356	45ACBL(1-5) 45ACCL(1-5) 45ACBR(1-5) 45ACCR(1-5) 045ACT 041D7675	47DCCR1 47DCCCL1 47DCCL1 47DCT 047DCT 41D8060 1D8060	50DCBL(1-5) 50DCCL(1-5) 50DCBR(1-5) 50DCCR(1-5) 1D8169-1 50DCTWF	50ACBL(1-5) 50ACCL(1-5) 50ACBR(1-5) 50ACCR(1-5) 1D8088-1 50ACTWF 045ACTWF	50DCBL(1-5)LK 50DCCL(1-5)LK 050DCTWFLK	50ACBL(1-5)LK 50ACCL(1-5)LK 050ACTWFLK 041-0036	050DCRJWF	041DJ002

IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:

	045DCT	045ACT	047DCT	050DCTWF	050ACTWF	050DCTWFLK	050ACTWFLK	050DCRJWF	041DJ002
--	--------	--------	--------	----------	----------	------------	------------	-----------	----------